

NAV Indicator

BENDIX

IN-244A

Circuit	Pin #	Notes
- NAV FLAG	1	
+ FROM	15	
+ LEFT	3	
+ NAV FLAG	13	
+ RIGHT	2	
+ TO	14	
C	10	Note 1
DIMMER	20	Note 2
DIMMER	21	Note 2
H	8	Note 1
POWER GROUND	19	
RESOLVER ROTOR C	17	
RESOLVER ROTOR H	16	
RESOLVER STATOR D	18	
RESOLVER STATOR E	6	
RESOLVER STATOR F	5	
RESOLVER STATOR G	4	
SPARE	12	
SPARE	22	
SPARE	23	
SPARE	24	
X	9	Note 1
Y	7	Note 1
Z	11	Note 1

Notes

1. Course datum CT option.
2. For 14 volts, 20 to Dimmer, 21 to ground. For 28 volts, 21 to Dimmer, 20 open.

For familiarization only. Consult the manufacturers current data.